


### SWITCH CONNECT BLE WALL SWITCH, IP20



## PRODUCT INFORMATION DOCUMENT

### FEATURES


- Requires CONNECT BLE GATEWAY
- Allows the user to activate scenes or settings at the push of a button
- Push button selection of up to three scenes with short, double and long presses
- Bluetooth technology gives long range of up to 25m
- CR2430 battery (included) gives up to 2 years operation
- Lifetime of >100,000 presses




	RCGBWS2
<b>Battery:</b>	1CR2430 3V DC
<b>Communication:</b>	Bluetooth Mesh
<b>Operating Range:</b>	25m open area
<b>IP:</b>	20
<b>Operation Temperature (°C):</b>	-10°C ≤ Ta ≤ +55°C
<b>Operating Humidity:</b>	<90%RH
<b>Battery Life:</b>	<2 years
<b>Dimensions WxHxD (mm):</b>	86x86x13mm
<b>Weight (kg):</b>	0.07

Product is certified to all the relevant standards.


Please contact our technical department for market specific compliances.



**Install/Replace battery:**  
Battery: Remove film



1. Push the front panel to the left to open



2. Remove old battery then push new CR2430 battery into slot



PLEASE NOTE: INFORMATION IN THIS DOCUMENT MAY BE SUBJECT TO CHANGE WITHOUT PRIOR NOTICE

IRE: TEL: +353 1 709 9000  
UK: TEL: 0800 973 220  
AUS: TEL: +61 7 3890 5444  
NZ: TEL: +050 8 533 335

WEB: WWW.ROBUS.COM  
WEB: WWW.ROBUS.COM  
WEB: WWW.ROBUS.COM.AU  
WEB: WWW.NZ\_PURCHASES@ROBUS.COM

LED GROUP EUROPE · AUSTRALIA · NEW ZEALAND · ASIA · MIDDLE EAST · AFRICA