


QUALITY PRODUCTS BY LED GROUP

EMERGENCY

LED MAINTAINED EXIT BOX



Codes: (Includes down arrow legend):	R8EMLED-01
Optional left and right arrow legend:	RCXL2/RCXR2
Power Consumption (W):	>3
Batteries (NiCad):	3.6v 1.8Ah
Discharge duration:	>3hrs after 24 hr charge
Light output (Im):	
LED Life L ₇₀ F ₁₀ (hrs):	30,000
Ambient Temperature Range (°C):	+5 ≤ Ta ≤ +25
IP Rating:	20
Guarantee (Yrs):	2
Box Qty:	1
Weight (Kg):	1.4

This LED exit box will satisfy the legal requirement to provide adequate emergency signage in our buildings. For all building types these fittings can be surface mounted on walls or ceilings. They combine the latest SMD LED and electronic driver technology to provide functional, energy efficient fittings. The fitting can be wired in maintained or non-maintained mode and can be switched by photocell if required to save energy while natural light is available.

- Offices
- Hospitals
- Entertainment Venues
- Public buildings
- Schools
- Shops and stores
- Hotels

- Health Centres
- Bars & Restaurants

FEATURES	BENEFITS
 Large clear running man down arrow legend with left and right legends available separately 	 Provides a viewing distance of up to 30m for safe exit and Options for emergency exit route direction indication
Two downward facing light windows	 Provides downward light to illuminate the area below the fitting for safe exit
Pressed steel white powder coated body	Aesthetically pleasing for installation in quality installations
Screwed legend retaining bar	 Quick and easy access to termination area for installation Left or right Running Man legend accessory can be quickly inserted
 Utilises high quality long life surface mount LED technology: Provides excellent light output Uses less than 3 watts of power Ensures an average LED life of 30,000 hours 	 Compared to T8 fluorescent: Comparable light output so is a one for one replacement Makes energy savings of over 60% No maintenance cost for replacement tubes
4 Screw terminal connection block for maintained or non-maintained wiring options	 Optional illumination modes: Permanently on Automatically switched on by photocell Solely emergency on mains failure
C/w NiCad rechargeable battery pack with green "charging" status LED	 Provides 3 hour emergency operation Provides up to 4 years backup under normal use Indicates when mains power is charging the unit
20mm gland entry points top & rear	Suitable for most wiring installation types
Rear BESA box mounting facility	Mounting on a BESA box where surface conduit supply is used
3 Keyhole slot mounting points	Allows fast and simple installation
2 year guarantee	 A quality energy efficient long life product Peace of mind

PLEASE NOTE - INFORMATION CONTAINED IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT PRIOR NOTICE



Western Retail Park Nangor Road Dublin 12 Ireland Tel +353 1 709 9000 Fax +353 1 709 9060 Email info@ledgrouprobus.com

www.ledgrouprobus.com www.robusdirect.com